



Certificate / Certificat Zertifikat / 合格証

WES 1505053 C002

exida hereby confirms that the:

**AccuTrak Position Monitor Series:
2200, 2300, 2600, 3000, 3200, 3300,
3400, 3500, 8300, 8400 and 8500**

**Westlock Controls
Saddle Brook, NJ - USA**

Have been assessed per the relevant requirements of:

IEC 61508 : 2010 Parts 1-7

and meets requirements providing a level of integrity to:

Systematic Capability: SC 3 (SIL 3 Capable)

Random Capability: Type A, Route 2_H Device

**PFH/PFD_{AVG} and Architecture Constraints
must be verified for each application**

Safety Function:

The Position Monitor switch(es) will change it's output when the attached Valve moves to the configured position.

Application Restrictions:

The unit must be properly designed into a Safety Instrumented Function per the Safety Manual requirements.

The manufacturer may use the mark:



Revision 3.1 December 21, 2021
Surveillance Audit Due
July 1, 2024



Evaluating Assessor

Certifying Assessor

WES 1505053 C002

Systematic Capability: SC 3 (SIL 3 Capable)

Random Capability: Type A, Route 2_H Device

PFH/PFD_{AVG} and Architecture Constraints must be verified for each application

Systematic Capability:

These Products have met manufacturer design process requirements of Safety Integrity Level (SIL) 3. These are intended to achieve sufficient integrity against systematic errors of design by the manufacturer.

A Safety Instrumented Function (SIF) designed with these products must not be used at a SIL level higher than stated.

Random Capability:

The SIL limit imposed by the Architectural Constraints must be met for each element. This Device meets *exida* criteria for Route 2_H.

Versions:

Series	Switch Quantity and Type (Option Code)
AccuTrak 2200	1 to 6 SPDT Microswitches (5) 1 to 4 DPDT Microswitches (6) 1 to 6 P&F Inductive Sensor (7) 1 to 6 Magnum Switches (9)
AccuTrak 2300	
AccuTrak 2600	
AccuTrak 3000	
AccuTrak 3200	
AccuTrak 3300	
AccuTrak 3400	
AccuTrak 3500	
AccuTrak 8300	
AccuTrak 8400	
AccuTrak 8500	

IEC 61508 Failure Rates¹ in FIT²

AccuTrak Series Switch Circuit Qty (Option Code)	λ_{SD}	λ_{Su}	λ_{DD}	λ_{DU}
1 Switch Circuit (5, 6, 7 or 9)	0	11	0	94
2 Switch Circuits (5, 6, 7 or 9)	0	23	0	119
3 Switch Circuits (5, 6, 7 or 9)	0	34	0	149
4 Switch Circuits (5, 6, 7 or 9)	0	45	0	174
6 Switch Circuits (5, 6, 7 or 9)	0	68	0	229
8 Switch Circuits (6)	0	80	0	239
1 Switch Circuit (5, 6, 7 or 9) w/PVST ³	11	0	86	8
2 Switch Circuits (5, 6, 7 or 9) w/PVST	23	0	110	9
3 Switch Circuits (5, 6, 7 or 9) w/PVST	34	0	139	10
4 Switch Circuits (5, 6, 7 or 9) w/PVST	45	0	163	11
6 Switch Circuits (5, 6, 7 or 9) w/PVST	68	0	216	13
8 Switch Circuits (6) w/PVST	80	0	225	14

¹ Failure Rates listed are only applicable if the switch contacts current is limited to 60% of the switches rated capacity and the end user has added external transient protection if being used with non-resistive loads.

² FIT = 1 failure / 10⁹ hours

³ PVST = Partial Valve Stroke Test of a final element Device

SIL Verification:

The Safety Integrity Level (SIL) of an entire Safety Instrumented Function (SIF) must be verified via a calculation of PFH/PFD_{AVG} considering redundant architectures, proof test interval, proof test effectiveness, any automatic diagnostics, average repair time and the specific failure rates of all products included in the SIF. Each subsystem must be checked to assure compliance with minimum hardware fault tolerance (HFT) requirements.

The following documents are a mandatory part of certification:

Assessment Report: WES 15/05-053 R002 V4 R2 (or later)

Safety Manual: TECHUK-78

**AccuTrak Position
Monitor Series: 2200,
2300, 2600, 3000, 3200,
3300, 3400, 3500, 8300,
8400 and 8500**



80 N Main St
Sellersville, PA 18960